

NASA TECH BRIEF

Goddard Space Flight Center



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Office, NASA, Code KT, Washington, D.C. 20546.

Fast Recharge Circuit for Q-Switched Lasers

The problem:

Q-switched, cavity-dumped lasers employ an electro-optic-effect cell, such as a Pockels cell, to alternately block and release the laser pulse. The Pockels cell requires a high-speed switching circuit that can apply and remove a high voltage. The circuit must switch at rates greater than 5 kHz, should be solid-state to eliminate warmup time, should provide a variable voltage waveform, and should allow polarity reversal.

The solution:

A new solid-state circuit employs complementary transistor switches and can meet all of the stated requirements.

How it's done:

A simplified schematic of the circuit is shown in Figure 1. A high voltage is applied to the input terminal by a dc supply (not shown), and controlling commands are applied to the Q-Switching (QS) and




Figure 1. Switching Circuit




Figure 2. Timing Diagram

cavity-dumping (CD) terminals. The QS command is applied at a time t_0 (see Figure 2) to the primary of the high-voltage isolating transformer T_1 . A triggering pulse is produced at the secondary T_1 and applied directly to fast switch #1 (a series-connected chain of 2N5401 pnp transistors). Before the signal is applied, the full high voltage is across the fast switch. Upon receipt of the QS command at t_0 , the switch shorts, connecting the anode of diode D_1 , and hence point A, rapidly to the high-voltage source. The rise time at point B (t_{rB}) may be determined from the following equation (if C_1 is $\gg C_B$).

$$t_{rB} = \sqrt{\pi(L)(C_B)}$$

$$\text{where } C_B = C_2 + C_{\text{CRYSTAL}} + C_{\text{VR2}} +$$

$$C_{\text{FAST SWITCH \#2}}$$

When the voltage level at B exceeds the voltage rating of zener diode VR_2 , further increase is clipped.

(continued overleaf)

At some later time t_2 , a pulse, applied at terminal CD by a pulse generator (not shown), causes fast switch #2 to short point B to ground. (Fast switch #2 is a series-connected chain of avalanche MPSU04 npn transistors.) This switching completes the generation of a high-voltage pulse suitable for the Pockels Cell. The polarity of the waveform applied to the Pockels Cell may be reversed simply by returning electrode Y to ground instead of the high-voltage source as shown. Another high-voltage pulse may be generated once the voltage at point A has returned to zero. Capacitor C1 isolates and protects fast switch #1 from #2 should a fault develop in either.

Note:

No further documentation is available. Specific questions, however, may be directed to:

Technology Utilization Officer
Goddard Space Flight Center
Code 207.1
Greenbelt, Maryland 20771
Reference: B73-10257

Patent status:

NASA has decided not to apply for a patent.

Source: R. L. Hansen of
GTE Sylvania Inc.
under contract to
Goddard Space Flight Center
(GSC-11510)